

SENIX Power Station

PORTABLE POWER



PS300

300W POWER STATION



Battery	18650 Lithium-ion Battery
Cycle Life	500 cycles ≥ 80%
Capacity	296 Wh (14.8V/20000mAh)
Power	300W rated,600W surge
DC Input	1*DC Input: 10V—25V,10V@5A,25V@2.5A adapter. Max: 60W
AC Output	2*AC Outputs,100-120VAC/60Hz
USB Output	1* USB-A Ports, 5V 2.4A Max, 1* Quick Charge USB-A Port(5V/3A,9V/2A,12V/1.5A,18W Max), 1* USB-C PD 3.0 Port,18W Max, 1* USB-C PD 3.0 Port,60W Max
DC Output	1*Auxiliary Power Output, 12V/10A 1*DC5521 Outputs,Share with car charging port, 120W max
Solar Panel Charger	300min (60W) Maximum support 60W
Car Port Charger	300min (60W) Maximum support 120W
Weight(Tool Only)	3.0 kg

PS600

600W POWER STATION



Battery	18650 Lithium-ion Battery
Cycle Life	500 cycles ≥ 80%
Capacity	518Wh (25.9V /20000mAh)
Power	600W rated 1300Max
DC Input	1*DC Input: 10-30V, 120W max, 5521DC port 1*PD Input: 5-20V,60W Max
AC Output	2*AC Outputs,100-120VAC/60Hz
USB Output	1* Quick Charge USB-A Port, 5-12V 18W Max 1* USB-A Ports and 1*USB-C port, shared output max 5V3A 1* USB-C PD Port: 5 to 20V, output 65W
DC Output	1*Auxiliary Power Output 12V 10A 120W Max 2*DC5521 Outputs, 13.6V 10A Share with car charging port, 120W Max
Solar Panel Charger	600min(60W) Maximum support 120W
Car Port Charger	600min(60W) Maximum support 120W
Weight(Tool Only)	5.0 kg

PS1200

1200W POWER STATION



Battery	33138 LFP
Cycle Life	1500 cycles ≥ 80%
Capacity	974.4Wh (22.4V/43.5Ah)
Power	1200W rated,2400 Max
DC Input	1*DC& Anderson support Solar Charge 10-30V 12Amax 240W Max 1*Adaptor DC charging input :10-30V/8A ,210W Max All outlets have the function of charging and discharging at the same time
AC Output	2*AC Outputs 100-120VAC/60Hz
USB Output	3* USB-A and 1* USB-C fast charges output, 5-12V 18W Max 1* USB-C PD Port: 5 to 20V, output 100W Max
DC Output	1*Auxiliary Power Output, 12V 10A 120W Max
Solar Panel Charger	1100min(60W) Maximum support 200W
Car Port Charger	660min(100w) Maximum support 120W
Weight(Tool Only)	8.9 kg